# Two in one





Compact Willidea Combi, designed into one elegant space saving cabinet


- Teletext, your access to a vide variety of information (not available for 14 PV182)
- · ShowViewiVidea+, for easy timer programming
- · Front ASY-connector, plug in your comcorder or game console
- · NTSC-Playback, enjoy VHS topes from the USA
- · Headphone connector, for unobtrousive listening
- · Simple and Easy to lastall, no need to install the VCRI

TY VIDEO

TELETEXT

**SHOWVIEW** 





## **Product Information**

# Reception

- . Tuning System: 1 Full-Cable PLL Tuner, UHF, VHF
- Tuning presets/entry system: 69/Channel & Frequency
- . Install Features: Aut Channel Install, Auto Store+, Manual

# Picture - Display/Processing

- Format/size(visual)" size(visual) cm: 4:3/14"(13V") 37/34cm
- · Picture Control: Brightness, Colour, Contrast, Sharpness, Tint

#### Sound

· Speaker/System/Power: Full Range 4"/Monol4W MPO, 2 Wrms

## User Interface

- · Multi Colour Menu: Cursor Control
- · Special Features: Auto Standby, Child Lock, Hotel mode
- Indicators front: On LED, Record LED, Timer Record LED

# **Computer Controlled Teletext**

(not available for 14PV182)

Standard: WST lev 1.5 W-Europe

#### Tape Deck

- •VCR System: VHS-HQ 2 Video Heads
- Head Cleaning Mode: Automatic, Manual
- · Stop to Pby Time: 0.4 sec.
- Tape Counter: Linear relative, Non linear NTSC Pb
- · Rewinding/Winding Time (E180): 170/260 sec.

# **Tape Functions**

- Play/Still Features: +1x,-1x, Repeat/Standard
- Fast Speed: +3x/-3x, +9x/-9x
- . VISS (Video Index Search Sys.): Next/Prev. index search

# **VCR Picture Quality**

- Noise Canceller/Resolution: Edge/HQ + >240 lines
- · Tracking System: Manual, Studio

#### **Programming**

- Number of Events: 6/month
- Rec. Contr. & Transm. Ident.; \* PDC/VPS
- Programming System: ShowView/V+, OTR
- · Record Speed: Standard Play, UK: also Long Play

# **Connectors Rear**

- EXT1: Euro CVBS, RGB in
- Antenna in: 75 Ohms (IECtype)

# **Connectors Front**

- EXT2: Cinch CVBS in, Cinch mono in
- Headphone Our: Mini-Jack 3.5mm, Mono

## General

- •Voltage / Frequency: 198-264V / 50/60Hz
- Operating/Standby Power Cons. InW: 48/8
- Backup Presets/Clock: >1 yrl>7 hrs
- Set Size (h x d x w) in mm: 385 x 363 x 375
- Packaging (h x d x w) in mm:  $520 \times 470 \times 450$
- Weight incl/excl. Packaging in kg. 16,8/14

# Accessories

- Documents and manuals: DFU, Guarantee doc, Screen Sticker
- Aux Equipm Supplied: Antenna, Batteries RC, Cable holder

#### Remote Control

- Remote Control typenr: RT770I10X
- \* according to version

# Product highlights

#### Automatic Channel Setup

The Combi tuner scans through television frequencies, automatically staring every active broadcosting channel into memory. Automatic channel preset can be repeated whenever desired, should new channels become available.

Channels can be manually added as well.

#### Teletext/Videotext

The built in Text-decoder gives you access to many different topics like: the latest news, the weather forecast or the IV-guide. It's a convenient source of up to date information,

# Unified Multifunction Infrared Remote

Controls all operating features and functions of both IV and VCR sections of this Combi from the convenience of your armchalt. This includes all special features, random channel access, and channel scan upldown.

#### Show View/VideoPlus Programming

Simplifies VCR programming by allowing you to simply enter ShowView/VideoFlus Code numbers found in many published television listings

#### • One-Touch Record

With the touch of a single button you can start a recording. Each touch of the RECORD button adds 30 minutes of additional recording time.

# Front Audio/Video Input Connector

Connect your Combi to the direct video output of a comcorder or video game to empy video entertainment.

#### • SCART Connector

The SCART connector also allows a SAT tuner or a PayTV decader to be connected to your Combi

#### · Headphone Socket

Plug in a personal headphone and enjoy your favorite movie, music video, video game without disturbing other family members in the room. The yeak is compatible with all standard 3.5 mm phona plugs.

#### · Sleep Timer

Automatically turns the Combi off at a preset time of up to 180-minutes from the time the feature is activated. Sleep timer settings at programmed in 15-minute incress.

#### Auto Head Cleaner

The video head is automatically cleaned each time a tope is inserted or removed, to maintain optimum picture performance during hath recording and playbock

# Full Auto Feature Package Incorporated into every PHILIPS Combi.

this complete package includes: automatic control for Power On when a tape is inserted, Automatic Studia Tracking, assuring proper algorithm of video and audio heads for perfect recordings and viewing every time; Auto Play, placing prerecorded tapes in the Play mode as soon as they're inserted in the unit; Auto Rewind, to rewind the cossette as soon as the tape reaches the end; Auto Eject at the end of the tape after rec so tapes are not inadvertently less in the Combi

	14 PV 182			14 PV 183		
	/05	/39	/58	/01	/08	/13
IV System off Air		FAL NG-L	PAL B/G-D/K.			
	PAL 1	SECAN BIG LIL	SECAN BYG-DYK	PAL R/G	PAL B/G	PAL BIG
Record/Phylack Std.	PAL	PAL-SEC-HESEC	FAL-HESEC	PAL	FAL	FAL
Additional Playback Std.	HTSC	NTSC	NTSC	NISC	NISC	MISC
Teletext		•			1	
* POCYPS	1 1	*	x			1
Tideo Langplay	x	-	-			•
CSD Henn Languages	G8,Fr,Sp,NI,D	Fr.GB,Es,MLD	GB,Fo,Rz,Hu,Cz,SI	D.M.Fr.It	IcSp,Pt,Fr,NI	GB,Sw,Me,Fi,Ck
Delvery Henr Language	English	French	English	Geman	fealun	English
Remete MITI6 /	101	164	101	tat	101	191

Subject to modification without notice

Incredible Surround is a Trademark of Philips Consumer Electronics Company. Show View and Video+ are a Trademark applied for by Gemstar Development Cooperation.



